

HMI User Right (password) Setting Instruction

1. Firstly set "System Preset Super Password"; Software Path: Application - Set Work Parameters - [Other Settings], set the position of the following figure:

Set OP PRM	
Com. set Network set Alarm/Other	Figure/Language
Cntrl Edit box to get focus c Gallery Location: RAM → Cntrl min font selection 8X16 → Screen saver time(Bra6 backlight off → 1 ↔ Comm. failure g Sound card HMI database storage options: RAM (Backup Inhibit 6 Minut →	Default value Default super passv 12345678 System other passv StartSee Initial(Master)Pic N 1 Input Keypad Siz 1# Screen Default bac Text default for 16X16 Text default backgro Text default foregrov
Trig conol Reg No. D:	0 (Current value!=0) 0 The[Current content] SecOprest: c
	Confirm(Y) plication Cancel (N

2. Make a function key on the user edit screen, double-click to set its property to: jump to No. 251: user configuration screen, check before the touch is valid, effectively select super, as shown in the three marked positions;

User Configure Screen	re	Scre	
	Function key attribute		F
User Configure Screenlogin logout	Position	Basic I Transpar Languag(Us	ser Configure Screensenior
	Left: 376 🔹	Touch effer anguag Us	er Configure Screensenior
	Top: 83	Set format Basic	function
	Property	Bordeluxury Jung	p to <mark>251#: User configura</mark>
	Wide: 55 🗘	Font SX16	ogin cogool et Rea
	High: 25	AlignMidd .	no com Link 1 *
	Backg	EffecLevel:Gen *	n typ: D - 7
	Prosp	C SerLevel:Syste	isterD:0
		Level:SenTo Level:Super Word:D1	Confirm(Y) Cancei()

3,After compiling and downloading to the touch screen, after setting different levels of passwords, you can select different levels of permissions according to your needs in the future editing process. A super password belongs to the user with the highest privilege, and only he can set all levels of password.